



telenor

Screenshots Cisco SPA504-G

Basic configuration for Cisco SPA504-G SIP single-user phone using dynamic registration towards Telenor IPT

The screenshot shows the Cisco SPA504G Configuration Utility interface. The browser address bar indicates the URL is 192.168.1.89/admin. The page title is "Small Business cisco SPA504G Configuration Utility". The navigation tabs include "Voice", "Call History", "Personal Directory", and "Attendant Console Status". The "Voice" tab is active, and the "User" sub-tab is selected. The configuration is for extension "Ext 1".

General

- Line Enable: yes
- Restrict MWI: no

NAT Settings

- NAT Mapping Enable: no
- NAT Keep Alive Enable: no

SIP Settings

- SIP Port: 5060
- SIP Debug Option: none

Call Feature Settings

- Message Waiting: no
- Mailbox ID: [empty]
- Auto Ans Page On Active Call: yes
- Enable Broadsoft Hoteling: no
- Default Ring: 1
- User ID with Domain: no
- Feature Key Sync: no
- Hoteling Subscription Expires: 3600

Proxy and Registration

- Proxy: ipt.telenor.com
- Register: yes
- Register Expires: 3600
- Make Call Without Reg: no
- Ans Call Without Reg: no

Buttons: Undo All Changes, Submit All Changes

© 2009 Cisco Systems, Inc. All Rights Reserved. SPA504G IP Phone

The screenshot shows the Cisco SPA504G Configuration Utility interface, continuing from the previous screenshot. The "User" sub-tab is still selected.

Subscriber Information

- Display Name: 22391670
- Password: [masked]
- Auth ID: [empty]
- User ID: +4722391670
- Use Auth ID: no

Audio Configuration

- Preferred Codec: G722
- Second Preferred Codec: G711a
- Silence Supp Enable: no
- Use Pref Codec Only: yes
- Third Preferred Codec: G711u
- DTMF Tx Method: Auto

Buttons: Undo All Changes, Submit All Changes

© 2009 Cisco Systems, Inc. All Rights Reserved. SPA504G IP Phone

Telenor, 05.05.17